

| rearTWIST | rearTWIST Tiny | Cable Jack Tiny | Cable Jack Panel | Hex Crimp in mm | Stripping Tool | | | | |
|-----------|-------------------|--------------------|---------------------|--------------------|-------------------|-----------|------------|------------|--------------|
| | | | | | | CS-BNC-RT | CS-BNC-LCS | CS-BNC-LCV | + CS-BNC-TCI |

Belden

| | | | | | | | | | |
|----------------------------|-------------|------------|------------|------------|------|---|---|---|---|
| 1277R, 1278R, 1279R | | NBTC75BNN5 | | | 4.53 | ● | - | - | ● |
| 1406B, 1407B, 1417B | | NBTC75BVV5 | | | 5.00 | ● | - | - | ● |
| 1426A, 1505A (ANH) | NBNC75BLP9 | | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| 1505F | NBNC75BJP9 | | | | 6.47 | ● | - | - | - |
| 1506A | NBNC75BIJ9 | | | | 5.41 | ● | - | - | - |
| 1520A, 1521A, 1522A, 179DT | | NBTC75BFI4 | NBTB75CFI4 | | 4.06 | ● | - | - | - |
| 1694A (ANH) | NBNC75BTU11 | | | | 7.36 | ● | - | - | - |
| 1694F | NBNC75BRU11 | | | | 7.36 | ● | - | - | - |
| 1695A | NBNC75BQP11 | | | | 6.47 | ● | - | - | - |
| 1855A | NBNC75BDD6 | | | | 4.53 | ● | - | - | - |
| 1865A | | NBTC75BXX6 | | | 5.00 | ● | - | - | - |
| 1855ENH | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| 7731A (ANH) | NBLC75BVZ17 | | | | 9.73 | - | - | ● | - |
| 8218 | | NBTC75BXX5 | | | 5.00 | ● | - | - | ● |
| 8241 | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| 8241F | NBNC75BLP9 | | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| 8281 | NBNC75BXY9 | | | | 8.23 | ● | - | - | - |
| 8281F | NBNC75BYY9 | | | | 8.23 | ● | - | - | - |
| 9221 | | NBTC75BLI4 | | | 4.06 | ● | - | - | - |
| 1794A | NBNC75BZV14 | | | | 8.23 | ● | - | - | - |

CANARE

| | | | | | | | | | |
|-------------|-------------|------------|--|------------|------|---|---|---|---|
| L-3CFB | NBNC75BHK7 | | | | 5.41 | ● | - | - | - |
| L-4CFB | NBNC75BLP9 | | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| L-5CFB | NBNC75BYY11 | | | | 8.23 | ● | - | - | - |
| LV-61S | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| LV-77S | NBNC75BYY9 | | | | 8.23 | ● | - | - | - |
| V(3-5)-3C | NBNC75BGG7 | | | | 5.00 | ● | - | - | - |
| V(3-5)-4CFB | NBNC75BJJ9 | | | | 5.41 | ● | - | - | - |
| V(3-5)-5C | NBNC75BRS9 | | | | 7.01 | ● | - | - | - |
| V(3-5)-5CFB | NBNC75BWS11 | | | | 7.01 | ● | - | - | - |
| L-1.5C2VS | | NBTC75BLI4 | | | 4.06 | ● | - | - | - |

COMMSCOPE

| | | | | | | | | | |
|--------------|-------------|------------|--|------------|------|---|---|---|---|
| 2065V | NBNC75BIJ9 | | | | 5.41 | ● | - | - | - |
| 2279V | NBNC75BQP11 | | | | 6.47 | ● | - | - | - |
| 5563 | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| 5565 | NBNC75BLP9 | | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| 5765 | NBNC75BTU11 | | | | 7.36 | ● | - | - | - |
| 7536 (03-05) | | NBTC75BXX6 | | | 5.00 | ● | - | - | - |
| 7538 | NBNC75BDD6 | | | | 4.53 | ● | - | - | - |

CANFORD

| | | | | | | | | | |
|------------------|-------------|--|--|--|------|---|---|---|---|
| SDV-M | NBTB75CNN5 | | | | 4.53 | ● | - | - | - |
| SDV, SDV-X, SDM | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| SDV-L, SDV-F | NBNC75BWS11 | | | | 7.01 | ● | - | - | - |
| SDV-HD | NBLC75BVZ17 | | | | 9.73 | ● | - | - | - |
| SDV-F-HD | NBNC75BWU13 | | | | 7.36 | ● | - | - | - |
| VCS (BBC PSF1/3) | NBNC75BLS7 | | | | 7.01 | ● | - | - | - |

| rearTWIST | rearTWIST Tiny | Cable Jack Tiny | Cable Jack Panel | Hex Crimp in mm | Stripping Tool |
|-----------|-------------------|--------------------|---------------------|--------------------|--|
| | | | | | CS-BNC-RT CS-BNC-LCS CS-BNC-LCV + CS-BNC-TCI |

DRAKA MULTIMEDIA CABLE

| | | | | | | | | |
|---|-------------|------------|-------------|------|---|---|---|---|
| 0.31 / 1.45 AF, 753-1304(2), 755-1302 | NBTC75BFI4 | NBTB75CFI4 | | 4.06 | ● | - | - | - |
| 0.41 / 1.9 AF, 753-1104, 755-1103, 755-1101 | NBTC75BNN5 | NBTB75CNN5 | | 4.53 | ● | - | - | - |
| 0.51 / 2.3 Dz, 757-1001, VADN 7243 | NBTC75BVX6 | | | 5.00 | ● | - | - | - |
| 0.6 / 2.8 AF, 0.6 L / 2.8 AF | NBNC75BFG7 | | | 5.00 | ● | - | - | - |
| 0.6 / 3.7, 0.6L / 3.7 | NBNC75BLP7 | | | 6.47 | ● | - | - | - |
| 0.6 / 3.7 Dz | NBNC75BLS7 | | | 7.01 | ● | - | - | - |
| 0.8 / 3.7 AF, 755-801(803, 804) | NBNC75BLP9 | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| 0.8 / 4.9 Dz | NBNC75BXY9 | | | 8.23 | ● | - | - | - |
| 1.0 / 4.8 AF, 755-901/5 | NBNC75BUU11 | | NBNB75GUU11 | 7.36 | ● | - | - | - |
| 1.2L / 4.8Dz, 1.2L / 4.95AF | NBNC75BWU13 | | | 7.36 | ● | - | - | - |
| 1.4 / 6.6 AF | NBLC75BSX14 | | | 9.73 | - | ● | - | - |
| 1.6 / 7.3AF | NBLC75BVZ17 | | | 9.73 | - | - | ● | - |

SUHNER

| | | | | | | | | |
|----------------|-------------|------------|------------|------|---|---|---|---|
| G02233 | | NBTC75BFI4 | NBTB75CFI4 | 4.06 | ● | - | - | ● |
| G04233D | NBNC75BLS7 | | | 7.01 | ● | - | - | - |
| S02223 | | NBTC75BLI4 | | 4.06 | ● | - | - | - |
| S04233, S04263 | NBNC75BLP9 | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| S05133-07 | NBNC75BTU11 | | | 7.36 | ● | - | - | - |
| S05163-02 | NBNC75BTU11 | | | 7.36 | ● | - | - | - |

Percon

| | | | | | | | | |
|---------------|-------------|------------|--|------|---|---|---|---|
| Percon VK2 | | NBTC75BNN5 | | 4.53 | ● | - | - | ● |
| Percon VK5 | NBNC75BFG7 | | | 5.00 | ● | - | - | - |
| Percon VK6 | NBNC75BLP9 | | | 6.47 | ● | - | - | - |
| Percon VK7 | NBNC75BUU11 | | | 7.36 | ● | - | - | - |
| Percon VK77 | NBNC75BTU11 | | | 7.36 | ● | - | - | - |
| Percon VK770F | NBNC75BWU13 | | | 7.03 | ● | - | - | - |
| Percon VK8 | NBLC75BSX14 | | | 9.73 | - | - | ● | - |
| Percon VK9 | NBLC75BVZ17 | | | 9.73 | - | - | ● | - |
| Percon VK95 | NBNC75BLP7 | | | 6.47 | ● | - | - | - |

Van Damme

| | | | | | | | | |
|-------------|-------------|-------------|--|------|---|---|---|---|
| 268-175-000 | NBNC75BUU11 | | | 7.36 | ● | - | - | - |
| 268-275-000 | NBNC75BJP9 | | | 4.06 | ● | - | - | - |
| 268-306-000 | NBNC75BLP9 | | | 6.47 | ● | - | - | - |
| 268-408-000 | | NBTC75BFI14 | | 6.47 | ● | - | - | ● |
| 268-475-000 | NBNC75BTU11 | | | 7.36 | ● | - | - | - |
| 268-675-000 | NBNC75BTU11 | | | 7.36 | ● | - | - | - |
| 278-475-000 | NBLC75BVZ17 | | | 9.73 | - | - | ● | - |
| 278-175-000 | NBNC75BUU11 | | | 7.36 | ● | - | - | - |
| 278-975-000 | NBNC75BLP9 | | | 6.47 | ● | - | - | - |
| 278-775-000 | | NBTC75BSS5 | | 4.53 | ● | - | - | ● |
| 278-075-000 | NBNC75BFG7 | | | 5.00 | ● | - | - | - |
| 278-075-006 | NBNC75BFG7 | | | 5.00 | ● | - | - | - |
| 278-375-000 | NBNC75BUU11 | | | 7.36 | ● | - | - | - |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |

| | rearTWIST | rearTWIST Tiny | Cable Jack Tiny | Cable Jack Panel | Hex Crimp in mm | Stripping Tool | | | |
|--|-----------|-------------------|--------------------|---------------------|--------------------|-------------------|--|--|--|
| | | | | | | + CS-BNC-TCI | | | |
| | | | | | | CS-BNC-LCS | | | |
| | | | | | | CS-BNC-LCV | | | |
| | | | | | | CS-BNC-RT | | | |

OTHERS

| | | | | | | | | | |
|------------------------------------|-------------|------------|------------|-------------|------|---|---|---|---|
| AT&T 735 | | NBTC75BSS5 | | | 4.53 | ● | - | - | ● |
| COMM-TEC RGBHV | | NBTC75BSS5 | | | 4.53 | ● | - | - | ● |
| Argosy Image 360 | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| Argosy Image 720 | NBNC75BLP9 | | | | 6.47 | ● | - | - | - |
| Argosy Image 1000 | NBNC75BUU11 | | | NBNB75GUU11 | 7.36 | ● | - | - | - |
| BBC PSF 1/3* | NBNC75BLS7 | | | | 7.01 | ● | - | - | - |
| BESCA France - Bengat | | NBTC75BNS4 | | | 4.53 | ● | - | - | - |
| CAE MC75 | | NBTC75BLI5 | NBTB75CLI5 | | 4.06 | ● | - | - | - |
| CAE MC75.39 | | NBTC75BVX6 | | | 5.00 | ● | - | - | - |
| CAE KX6A | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| CAE VCB75 | NBNC75BNP9 | | | | 6.47 | ● | - | - | - |
| CAE VCB 100 | NBNC75BXU13 | | | | 7.36 | ● | - | - | - |
| Cordial CVI 3-7 | NBNC75BFG7 | | | | 4.53 | ● | - | - | - |
| Cordial CVI 06-28 | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| Cordial CVI (CVM) 06-37 | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| COVID CVD 1300-1500 | | NBTC75BLI5 | NBTB75CLI5 | | 4.06 | ● | - | - | - |
| Eupen 705 CRT 5V-HS | NBNC75BTS11 | | | | 7.36 | ● | - | - | - |
| Extron BNC-5HR | | NBTC75BNN5 | NBTB75CNN5 | | 4.53 | ● | - | - | - |
| Extron BNC-5RC | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| Fuzion SD-1 | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| Fuzion SD-1-LL | NBNC75BWS11 | | | | 7.01 | ● | - | - | - |
| GEPCO VPM2000 | NBNC75BLP9 | | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| GEPCO VSD2001 | NBNC75BTU11 | | | | 7.36 | ● | - | - | - |
| Helix 734 | NBNC75BNP9 | | | | 6.47 | ● | - | - | - |
| Helix 735 | | NBTC75BSS5 | | | 4.53 | ● | - | - | - |
| Hirschmann KOKA 712Cu | NBNC75BTS9 | | | | 6.47 | ● | - | - | - |
| Kansai 3C-5S | NBNC75BFH6 | | | | 5.00 | ● | - | - | - |
| KLOTZ V06/28, VMXx75Y | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| KLOTZ V06/37 | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| KLOTZ V10/48 | NBNC75BUU11 | | | NBNB75GUU11 | 7.36 | ● | - | - | - |
| KLOTZ V16/72 | NBNC75BVZ17 | | | | 9.73 | ● | - | - | - |
| KROSCHU (341 270, 341 280) | | | NBTC75BLI4 | | 4.06 | ● | - | - | - |
| Nexans HF 75 0.6/2.9 02YS(ST)CH | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| Nexans HF 75 1.6/7.2 02Y(ST)C(ST)H | NBNC75BVZ17 | | | | 9.73 | ● | - | - | - |
| Nexans HF 75 0.6/3.7 2YCY | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| Proel HPC 805 | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| Proel HPC 810 | NBNC75BLP9 | | | | 6.47 | ● | - | - | - |
| Proel HPC 820 | NBNC75BFH6 | | | | 5.00 | ● | - | - | - |
| RG11 | NBNC75BVZ17 | | | | 9.73 | - | - | ● | - |
| RG59B/U | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| RG179B/U | | NBTC75BLI4 | | | 4.06 | ● | - | - | ● |
| SOMMER 600-0051 (M/L/S) | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| SOMMER 600-0054 (M/L/S) | NBNC75BLP7 | | | | 6.47 | ● | - | - | - |
| SOMMER 600-0101M | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| SOMMER 600-0104M | NBNC75BFG7 | | | | 5.00 | ● | - | - | - |
| SOMMER 600-162(F) | NBNC75BLP9 | | | | 6.47 | ● | - | - | - |
| SOMMER 600-025* -03 (05) | | NBTC75BLI5 | NBTB75CLI5 | | 4.06 | ● | - | - | - |
| SOMMER 600-0701 | | NBTC75BLI5 | NBTB75CLI5 | | 4.06 | ● | - | - | - |
| SOMMER 600-020* -03 (05) | | NBTC75BLI5 | NBTB75CLI5 | | 4.06 | ● | - | - | - |
| SOMMER 600-0451 | NBNC75BLP9 | | | NBNB75GLP9 | 6.47 | ● | - | - | - |
| SOMMER 600-0751 | | NBTC75BVX6 | | | 5.00 | ● | - | - | - |
| Wisi MK 99A | NBNC75BWS12 | | | | 7.01 | ● | - | - | - |
| ZNK CM14B | | NBTC75BFI4 | NBTB75CFI4 | | 4.06 | ● | - | - | - |

* Registered trademark of BBC

| | Inner Conductor | Insulator | Cable O.D. in mm | Pin crimp mm (square) | Hex crimp mm | Stripping Tool | | | |
|--|-----------------|-----------|------------------|-----------------------|--------------|----------------|------------|------------|--------------|
| | | | | | | CS-BNC-RT | CS-BNC-LCS | CS-BNC-LCV | + CS-BNC-TCI |

rearTWIST

| | | | | | | | | | |
|-------------|-------|-------|--------|-------------------|------|---|---|---|---|
| NBLC75BVZ17 | < 1.7 | < 8.0 | < 10.4 | 1.75 (Hex crimp) | 9.73 | - | - | ● | - |
| NBLC75BSX14 | < 1.4 | < 6.6 | < 9.5 | 1.75 (Hex crimp) | 9.73 | - | - | ● | - |
| NBNC75BDD6 | < 0.6 | < 2.8 | < 4.3 | 1.6 | 4.53 | ● | - | - | - |
| NBNC75BFG7 | < 0.7 | < 3.1 | < 4.7 | 1.6 | 5.00 | ● | - | - | - |
| NBNC75BFH6 | < 0.6 | < 3.1 | < 4.9 | 1.6 | 5.00 | ● | - | - | - |
| NBNC75BGG7 | < 0.7 | < 3.2 | < 4.7 | 1.6 | 5.00 | ● | - | - | - |
| NBNC75BHK7 | < 0.7 | < 3.3 | < 5.6 | 1.6 (or 1.75 Hex) | 5.41 | ● | - | - | - |
| NBNC75BIJ9 | < 0.9 | < 3.6 | < 5.3 | 1.6 | 5.41 | ● | - | - | - |
| NBNC75BJJ9 | < 0.9 | < 3.8 | < 5.3 | 1.6 | 5.41 | ● | - | - | - |
| NBNC75BJP9 | < 0.9 | < 3.8 | < 6.3 | 1.6 | 6.47 | ● | - | - | - |
| NBNC75BLP7 | < 0.7 | < 3.8 | < 6.3 | 1.6 | 6.47 | ● | - | - | - |
| NBNC75BLP9 | < 0.9 | < 3.8 | < 6.3 | 1.6 | 6.47 | ● | - | - | - |
| NBNC75BLS7 | < 0.7 | < 3.8 | < 6.9 | 1.6 | 7.01 | ● | - | - | - |
| NBNC75BNP9 | < 0.9 | < 4.1 | < 6.3 | 1.6 | 6.47 | ● | - | - | - |
| NBNC75BQP11 | < 1.1 | < 4.5 | < 6.3 | 1.6 | 6.47 | ● | - | - | - |
| NBNC75BRS9 | < 0.9 | < 4.8 | < 6.9 | 1.6 | 7.01 | ● | - | - | - |
| NBNC75BTS9 | < 0.9 | < 4.7 | < 6.9 | 1.6 | 7.01 | ● | - | - | - |
| NBNC75BTS11 | < 1.1 | < 4.7 | < 6.9 | 1.6 | 7.01 | ● | - | - | - |
| NBNC75BTU11 | < 1.1 | < 4.7 | < 7.3 | 1.6 | 7.36 | ● | - | - | - |
| NBNC75BTU13 | < 1.3 | < 4.7 | < 7.3 | 1.6 | 7.36 | ● | - | - | - |
| NBNC75BUU11 | < 1.1 | < 4.9 | < 7.3 | 1.6 | 7.36 | ● | - | - | - |
| NBNC75BRU11 | < 1.1 | < 4.7 | < 7.3 | 1.6 | 7.36 | ● | - | - | - |
| NBNC75BWS11 | < 1.1 | < 5.1 | < 6.9 | 1.6 | 7.01 | ● | - | - | - |
| NBNC75BWS12 | < 1.2 | < 5.1 | < 6.9 | 1.6 | 7.01 | ● | - | - | - |
| NBNC75BWU13 | < 1.4 | < 5.1 | < 7.3 | 1.6 | 7.36 | ● | - | - | - |
| NBNC75BXU13 | < 1.4 | < 5.3 | < 7.3 | 1.6 | 7.36 | ● | - | - | - |
| NBNC75BXY9 | < 0.9 | < 5.3 | < 8.0 | 1.6 | 8.23 | ● | - | - | - |
| NBNC75BY9 | < 0.9 | < 5.2 | < 8.0 | 1.6 | 8.23 | ● | - | - | - |
| NBNC75BYY11 | < 1.1 | < 5.2 | < 8.0 | 1.6 | 8.23 | ● | - | - | - |
| NBNC75BZV14 | < 1.4 | < 5.2 | < 8.0 | 1.6 (or 1.75 Hex) | 8.23 | ● | - | - | - |

rearTWIST TINY

| | | | | | | | | | |
|------------|-------|-------|-------|-----|------|---|---|---|---|
| NBTC75BFI4 | < 0.4 | < 1.6 | < 2.9 | 1.6 | 4.06 | ● | - | - | ● |
| NBTC75BLI4 | < 0.4 | < 1.8 | < 2.9 | 1.6 | 4.06 | ● | - | - | ● |
| NBTC75BLI5 | < 0.5 | < 1.8 | < 2.9 | 1.6 | 4.06 | ● | - | - | ● |
| NBTC75BNN5 | < 0.5 | < 2.0 | < 3.1 | 1.6 | 4.53 | ● | - | - | ● |
| NBTC75BNS4 | < 0.4 | < 2.0 | < 3.5 | 1.6 | 4.53 | ● | - | - | ● |
| NBTC75BSS5 | < 0.5 | < 2.3 | < 3.4 | 1.6 | 4.53 | ● | - | - | ● |
| NBTC75BVV5 | < 0.5 | < 2.5 | < 3.8 | 1.6 | 5.00 | ● | - | - | ● |
| NBTC75BVX6 | < 0.6 | < 2.5 | < 4.0 | 1.6 | 5.00 | ● | - | - | ● |
| NBTC75BXX5 | < 0.5 | < 2.6 | < 4.0 | 1.6 | 5.00 | ● | - | - | ● |
| NBTC75BXX6 | < 0.6 | < 2.6 | < 4.0 | 1.6 | 5.00 | ● | - | - | ● |

CABLE JACKS (TINY & PANEL VERSION)

| | | | | | | | | | |
|-------------|-------|-------|-------|-----|------|---|---|---|---|
| NBTB75CFI4 | < 0.4 | < 1.6 | < 2.9 | 1.6 | 4.06 | ● | - | - | ● |
| NBTB75CNN5 | < 0.5 | < 2.0 | < 3.1 | 1.6 | 4.53 | ● | - | - | ● |
| NBTB75CLI5 | < 0.5 | < 1.8 | < 2.9 | 1.6 | 4.06 | ● | - | - | ● |
| NBNB75GLP9 | < 0.9 | < 3.8 | < 6.3 | 1.6 | 6.47 | ● | - | - | ● |
| NBNB75GUU11 | < 1.1 | < 4.9 | < 7.3 | 1.6 | 7.36 | ● | - | - | ● |
| NBNB75ILP9 | < 0.9 | < 3.8 | < 6.3 | 1.6 | 6.47 | ● | - | - | ● |
| NBNB75IUU11 | < 1.1 | < 4.9 | < 7.3 | 1.6 | 7.36 | ● | - | - | ● |